



FRONTIER 9.18
LSNP FORM
VER 1.0

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
Section: ADMIN Number of Occurrences:							
1	PON - Purchase Order Number	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
2	VER - Version Identification	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
3	AN - Account Number	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
4	ATN - Account Telephone Number	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
5	LQTY - Loop Quantity		N	1-5		1. If populated and dl >5 characters, Return error FTRLSNP001 INVALID LOOP QUANTITY DATA LENGTH. 2. If populated and dc≠ Numeric return error FTRLSNP002 INVALID DATA, LOOP QUANTITY MUST BE NUMERIC. 3.If not populated return error message FTRLSNP003 LOOP QUANTITY REQUIRED	R
6	NPQTY - Number Portability Quantity		N	1-5		1 .If populated and dl >5 characters, Return error FTRLSNP004 INVALID DATA NPQTY LENGTH. 2.If populated and dc≠ Numeric return error FTRLSNP005 INVALID NPQTY DATA, MUST BE NUMERIC. 3.If not populated return error message FTRLSNP008 NPQTY REQUIRED	R
7	PG_of_ - Page _ of _	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
Section: Service Details Number of Occurrences:							
8	LOCNUM - Location Number		N	1-3		1.If populated and dl >than 3 characters, Return error FTRLSNP006 INVALID LOCNUM DATA	R

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>LENGTH.</p> <p>2. If populated and dc ≠ Numeric return error FTRLSNP007 INVALID DATA, LOCNUM MUST BE NUMERIC.</p> <p>3. If not populated return error FTRLSNP009 LOCNUM REQUIRED.</p>	
9	LNUM - Line Number		N	1-5		<p>1. If populated and dl >5 characters, Return error FTRLSNP010 INVALID LNUM LENGTH MAY NOT EXCEED 5 CHARACTERS.</p> <p>2.If populated and dc ≠ Numeric return error FTRLSNP011 INVALID DATA, LNUM MUST BE NUMERIC.</p> <p>3. If not populated return error FTRLSNP012 LNUM REQUIRED.</p>	R
10	NPI - Number Portability Indicator		A	1-1	A	<p>1.If populated and vv ≠ A return error FTRLSNP013 ONLY VALID VALUE A.</p>	O
11	LNA - Line Activity		A	1-1	D or V	<p>1.If populated and LSR ADMIN ACT = "V", and LNA ≠ V or D RETURN ERROR FTRLSNP014 - ONLY LNA VALID VALUE D OR V.</p> <p>2. If not populated return error message FTRLSNP134 LNA REQUIRED</p>	R
12	RL - Reuse Loop		A	1-1	Y = Yes	<p>1.If not populated and the 2nd position of LSR.ADMIN TOS = "F" and the LNA field = "V" and the OECCKT field is populated. Return error FTRLSNP018 REUSE LOOP REQUIRED</p> <p>2. If populated and ((the 2nd character of the LSR.ADMIN TOS ≠ "F") or (the LNA field ≠ "V") or</p>	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						(OECCKT is not populated)) return error FTRLSNP019 REUSE LOOP PROHIBITED 3. If populated and vv ≠ Y return error FTRLSNP020 INVALID REUSE LOOP VALUE. MUST BE Y	
13	LMT - Loop Modification Type	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
14	BTRL - Bridged Tap Removal Location	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
15	CKR - Customer Circuit Reference		A/N Ampersand, Apostrophe, Asterisk, Parentheses , Colon, Comma, Dollar Sign, Hyphen, Number Sign, Percent, Plus Sign, Quote, Semicolon, Space, Period	1-41		1. If not populated and LNA = "V", and NPT ="D" or "E", return error FTRLSNP015 CUSTOMER CIRCUIT REFERENCE REQUIRED 2. If populated and dl >41 Characters, return error FTRLSNP016 INVALID DATA LENGTH CKR CANNOT EXCEED 41 CHARACTERS. 3. If populated and dc special characters ≠ Ampersand, Apostrophe, Asterisk, Parentheses, Colon, Comma, Dollar Sign, Hyphen, Number Sign, Percent, Plus Sign, Quote, Semicolon, Space, Period return error FTRLSNP017 THE ONLY CHARACTERS ALLOWED ARE A/N AMPERSAND, APOSTROPHE, ASTERISK, PARENTHESES, COLON, COMMA, DOLLAR SIGN, HYPHEN, NUMBER SIGN, PERCENT, PLUS SIGN, QUOTE, SEMICOLON, SPACE PERIOD	O
16	TSP - Telecommunications Service Priority		A/N - Hyphen.	9-12		1. If populated and the 1st position of the LSR.ADMIN.TOS = "2". RETURN ERROR FTRLSNP025 TELECOMMUNICATIONS SERVICE PRIORITY	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>PROHIBITED</p> <p>2.If populated and special characters ≠ hyphen return error FTRLSNP026 ONLY SPECIAL TSP DATA CHARACTERISTICS ALLOWED IS HYPHEN.</p> <p>3. If populated and dl <9 or >12 return error FTRLSNP027 TSP INVALID DATA LENGTH.</p>	
17	TNT - Test and Tag Requested		A	1-1	D	<p>1 If populated and EU.LOC.STATE NOT =PA return error FTRLSNP028 INVALID FOR STATE</p> <p>2. If populated and position 2 of LSR.ADMIN.TOS=2 and position 3 of LSR.ADMIN.TOS= 1,2,3,4,6 or R return error message FTRLSNP029 TNT PROHIBITED.</p> <p>3. If populated and vv ≠ D return error message FTRLSNP030 INVALID TNT VALUE. ONLY VALUE CAN BE D</p>	O
18	LRN - Location Routing Number		N	10-10		<p>1. If populated and dl ≠ 10 characters return error FTRLSNP031 INVALID LRN DATA LENGTH.</p> <p>2. If populated and dc ≠ Numeric return error FTRLSNP032 INVALID LRN DATA CHARACTERISTIC. MUST BE NUMERIC</p>	O
19	TDT - Ten Digit Trigger		A	1-1	Y=YES	<p>1.If populated and vv ≠ Y return error FTRLSNP033 INVALID VALUE TDT ONLY VALID VALUE Y</p>	O
20	SAN - Subscriber Authorization Number		A/N Ampersand, Apostrophe, Asterisk,	1-30		<p>1. If populated and dl > 30 characters return error FTRLSNP035 SAN CANNOT EXCEED 30 CHARACTERS.</p>	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
			Colon, Comma, Dollar Sign, Hyphen, Number Sign, Parentheses , Period, Quotation Marks, Space.			2.If populated and dc ≠ A/N Ampersand, Apostrophe, Asterisk, Parentheses, Colon, Comma, Dollar Sign, Hyphen, Number Sign, Percent, Plus Sign, Quote, Semicolon, Space return error FTRLSNP135 THE ONLY CHARACTERS ALLOWED ARE A/N AMPERSAND, APOSTROPHE, ASTERISK, PARENTHESSES, COLON, COMMA, DOLLAR SIGN, HYPHEN, NUMBER SIGN, PERCENT, PLUS SIGN, QUOTE, SEMICOLON, SPACE.	
21	ECCKT - Exchange Company Circuit ID	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
22	OECCKT - Out Exchange Company Circuit ID		A/N virgules.	1-41		<p>1. If not populated and RL field is populated return error FTRLSNP021 OECCKT REQUIRED WHEN REUSE FIELD IS POPULATED.</p> <p>2. If populated and RL field is not populated return error FTRLSNP022 OECCKT PROHIBITED WHEN REUSE LOOP FIELD NOT POPULATED.</p> <p>3. If populated and special characters ≠ virgules return error FTRLSNP023 ONLY OECCKT SPECIAL CHARACTERS ALLOWED ARE VIRGULES.</p> <p>4. If populated and dl >than 41 return error FTRLSNP024, INVALID OECCKT DATA LENGTH</p>	O
23	RESID - Response Identifier	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
24	CFA - Connecting Facility Assignment		A/N Hyphen, Period,	1-42		1.If not populated and EU.LOC.STATE=DE,DC,MD,NJ,PA,VA,WV and position 2 of the LSR ADMIN TOS= "4" and	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
			Space.			<p>position 3 of the LSR ADMIN TOS= 7 or 8 return error message FTRLSNP036 CFA REQUIRED</p> <p>2. If populated and dl > 42 characters return error message FTRLSNP037 INVALID CFA DATA LENGTH</p> <p>3. If populated and special characters ≠ Hyphen, Period, Space return error FTRLSNP038 ONLY CFA SPECIAL CHARACTERS ALLOWED ARE HYPHEN, PERIOD AND SPACE.</p>	
25	CCEA - Cross Connect Equipment Assignment	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
25A	CTI - Connection Type Indicator		A	1-1	Valid Entries B	<p>1.If populated and LSR ADMIN SLI ≠ "S" and (position 2 of LSR ADMIN TOS ≠ "F") and (LNA ≠ "V") and (RL ≠ "Y") Return error FTRLSNP039 CONNECTION TYPE INDICATOR PROHIBITED</p> <p>2.If populated and vv ≠ B return error FTRLSNP040 VALID CTI VALUE B</p> <p>3. If not populated and LSR.ADMIN.SLI = S and position 2 of LSR.ADMIN.TOS = F and LNA = V and RL = Y return error message: FTRLSNP125 CTI REQUIRED</p> <p>4. If populated and EU.LOC.STATE=MD, VA, WV, DC, DE, PA, NJ and SYSTEM ID, SHELF and CHAN/PAIR are not populated return error message FTRLSNP136 CTI REQUIRES SYSTEM ID, SHELF AND CHAN/PAIR</p> <p>5. If populated and EU.LOC.STATE=CT, NY, MA,</p>	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						VT, NH, RI, ME and CABLE ID and CHAN/PAIR are not populated return error message FTRLSNP137 CTI REQUIRES CABLE ID AND CHAN/PAIR	
26	SYSTEM ID - System Identification		A/N	5-5		<p>1. If not populated and EU.LOC.STATE=MD, VA, WV, DC, DE, PA, NJ and (((LNA=V) and (NPT=D, E)) and (LSR.ADMIN.SLI=S) and ((position 2 of LSR.ADMN.TOS=1, 2, 3, W, X) or (CTI=B) or (position 2 of LSR.ADMN TOS=4 and position 3 of LSR.ADMN TOS=4))), then return error: FTRLSNP041 SYSTEM ID REQUIRED</p> <p>2. If populated and EU.LOC.STATE=MD, VA, WV, DC, DE, PA, NJ and (((LNA ≠ V) or (NPT ≠ D, E)) or (LSR.ADMIN.SLI ≠ S) or ((position 2 of LSR.ADMN .TOS ≠ 1, 2, 3, W, X) and (CTI ≠ B) and (position 2 of LSR.ADMN .TOS ≠ 4 or position 3 of LSR.ADMN .TOS ≠ 4))), then return error: FTRLSNP042 SYSTEM ID PROHIBITED</p> <p>3.If populated and format ≠ AAANN return error message FTRLSNP044 SYSTEM ID MUST BE 3 ALPHA FOLLOWED BY 2 NUMERIC.</p> <p>4.If populated and dl ≠ 5 return error message FTRLSNP043 SYSTEM ID MUST BE 5 CHARACTERS 3 ALPHA FOLLOWED BY 2 NUMERIC.</p>	O
27	CABLE ID - Cable Identification		A/N Ampersand, Apostrophe, Asterisk, Colon, Comma,	5-5		<p>1. If not populated and EU.LOC.STATE=CT, NY, MA, VT, NH, RI, ME and (((LNA=V) and (NPT=D, E)) and (LSR.ADMIN.SLI=S) and ((position 2 of LSR.ADMIN.TOS=1, 2, 3, W, X) or (CTI=B) or (position 2 of LSR.ADMIN TOS=4 and position 3 of LSR.ADMIN TOS=4))), then return error:</p>	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
			Dollar Sign, Hyphen, Number Sign, Parentheses, Period, Quotation Marks, Space, Percent Sign, Plus Sign, Semicolon, Virgule, At Sign.			<p>FTRLSNP045 CABLE ID REQUIRED</p> <p>2. If populated and EU.LOC.STATE= CT, NY, MA, VT, NH, RI, ME and (((LNA ≠ V) or (NPT ≠ D, E)) or (LSR.ADMIN.SLI ≠ S) or ((position 2 of LSR.ADMIN .TOS ≠ 1, 2, 3, W, X) and (CTI ≠ B) and (position 2 of LSR.ADMIN TOS ≠ 4 or position 3 of LSR.ADMIN TOS ≠ 4))), then return error: FTRLSNP046 CABLE ID PROHIBITED</p> <p>3. If populated and dl ≠ 5 characters return error message FTRLSNP047 CABLE ID MUST BE 5 CHARACTERS</p> <p>4. If populated and Special Characters ≠ Ampersand, Apostrophe, Asterisk, Colon, Comma, Dollar Sign, Hyphen, Number Sign, Parentheses, Period, Quotation Marks, Space, Percent Sign, Plus Sign, Semicolon, Virgule, At Sign. Return error message FTRLSNP050 INVALID CABLE ID DATA, THE ONLY SPECIAL CHARACTERS ALLOWED ARE AMPERSAND, APOSTROPHE, ASTERISK, COLON, COMMA, DOLLAR SIGN, HYPHEN, NUMBER SIGN, PARENTHESSES, PERIOD, QUOTATION MARKS, SPACE, PERCENT SIGN, PLUS SIGN, SEMICOLON, VIRGULE, AT SIGN</p>	
28	CBCID - Cross Box Cable Identification		A/N	1-10		<p>1.If not populated (((the LSR.ADMIN.SLI="B") and (the LNA field ="V") and (the NPT field ="D" or "E")) and (the 2nd character of LSR.ADMIN.TOS field = "1", "2", "3", "4", or "R")) return error FTRLSNP051-CROSS BOX CABLE IDENTIFICATION REQUIRED</p>	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>2.If populated and (((the LSR.ADMIN.SLI ="B") and (the LNA field = "V") and (the NPT field = "D" or "E")) and (the 2nd character LSR.ADMIN.TOS field ≠ "1", "2", "3", "4", or "R")) return error FTRLSNP052 -CROSS BOX CABLE IDENTIFICATION PROHIBITED.</p> <p>3. If populated and dl > 10 characters return error FTRLSNP053 INVALID CROSS BOX CABLE IDENTIFICATION DATA LENGTH.</p>	
28A	CBCID2 - Cross Box Cable Identification 2		A/N	1-10		<p>1. If not populated and the LNA field = "V" and LSR.ADMIN.SLI = "B" and NPT = D or E and the 2nd position of LSR.ADMIN.TOS = "3" or "4" or R Return Error FTRLSNP054 CROSS BOX CABLE IDENTIFICATION 2 REQUIRED</p> <p>2. If populated and LNA ≠ V or LSR.ADMIN.SLI ≠ B" or (NPT ≠ D or E) or (position 2 of LSR.ADMIN.TOS ≠ "3" or "4" or R). RETURN ERROR FTRLSNP055 CROSS BOX CABLE IDENTIFICATION 2 PROHIBITED</p> <p>3. If populated and dl > than 10 characters, return error FTRLSNP056 INVALID CBCID2 DATA LENGTH.</p>	O
29	SHELF - Shelf		N	2-2		<p>1. If not populated and EU.LOC.STATE=MD, VA, WV, DC, DE, PA, NJ and (((LNA=V) and (NPT=D, E)) and (LSR.ADMIN.SLI=S) and ((position 2 of LSR.ADMIN.TOS=1, 2, 3, W, X) or (CTI=B) or (position 2 of LSR.ADMIN.TOS=4 and position 3of LSR.ADMIN.TOS=4))), then return error: FTRLSNP057 SHELF REQUIRED</p>	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>2. If populated and EU.LOC.STATE=MD, VA, WV, DC, DE, PA, NJ and (((LNA ≠ V) or (NPT ≠ D, E)) or (LSR.ADMIN.SLI ≠ S) or ((position 2 of LSR.ADMIN.TOS ≠ 1, 2, 3, W, X) and (CTI ≠ B) and (position 2 of LSR.ADMIN.TOS ≠ 4 or position 3 of LSR.ADMIN.TOS ≠ 4))), then return error: FTRLSNP058 SHELF PROHIBITED</p> <p>3.DELETE RULE</p> <p>4. If populated and dl ≠ 2 return error message FTRLSNP059 SHELF MUST BE 2 NUMERIC CHARACTERS.</p> <p>5. If populated and dc ≠ N return error message FTRLSNP131 SHELF MUST BE 2 NUMERIC CHARACTERS.</p>	
30	SLOT - Slot		A/N	1-4		<p>1. If populated and dl > 4 return error FTRLSNP048 INVALID DATA SLOT LENGTH.</p> <p>2. If populated and SHELF is not populated return error message FTRLSNP122 SLOT IS PROHIBITED</p>	O
31	SPORT - Slot Port	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
32	RELAY RACK - Relay Rack		A/N	1-10		1. If populated and dl > 10 return error FTRLSNP123 INVALID DATA RELAY RACK LENGTH.	O
33	CHAN/PAIR - Channel/Pair		A/N	5-5		1. If not populated and (((LNA=V) and (NPT=D, E)) and (LSR.ADMIN.SLI=S) and ((position 2 of LSR.ADMIN.TOS=1, 2, 3, W, X) or (CTI=B) or (position 2 of LSR.ADMIN.TOS=4 and position 3 of LSR.ADMIN.TOS=4))), then return error:	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>FTRLSNP060 CHAN/PAIR REQUIRED</p> <p>2. If populated and (((LNA ≠ V) or (NPT ≠ D, E)) or (LSR.ADMIN.SLI ≠ S) or ((position 2 of LSR.ADMIN.TOS ≠ 1, 2, 3, W, X) and (CTI ≠ B) and (position 2 of LSR.ADMIN.TOS ≠ 4 or position 3 of LSR.ADMIN.TOS ≠ 4))), then return error: FTRLSNP061 CHAN/PAIR PROHIBITED</p> <p>3. If populated and dl ≠ 5 return error FTRLSNP062 CHAN/PAIR MUST BE 5 CHARACTERS.</p> <p>4. If populated and vv not in range 00001 - 09999.and EU.LOC.STATE= CT,MA,ME,NH,NY, RI, VT return error FTRLSNP063 CHAN/PAIR MUST BE IN RANGE OF 00001 - 09999</p> <p>5. If populated and vv not in range 00001 - 00999 and EU.LOC. STATE = DE,DC,MD,NJ,PA,VA , WV return error FTRLSNP064 CHAN/PAIR MUST BE IN RANGE OF 00001 - 00999.</p>	
34	UNIT - Unit	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
34A	RESZONE - Resistance Zone		A	1-1	Y	<p>1.If populated and 2nd position of the LSR.ADMIN.TOS = "6" or "Z" or the LSR.ADMIN.SLI = "H", and EU.LOC.STATE. =NY return error FTRLSNP065 RESZONE PROHIBITED</p> <p>2.If populated and vv ≠ Y return error FTRLSNP066 RESZONE VALID VALUE IS Y.</p>	O
34B	LOOPQUAL - Loop Qualification Status		A	1-1	C R	1. If not populated and the LNA field = "V" and the NPT field = "D" or "E" and the 2nd character of the	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>LSR.ADMIN.TOS = "2" and the 3rd character of the LSR.ADMIN.TOS = "1", "2", "3", "4" or "6" and the LSR.ADMIN.SLI = "C", "S" or "V" return error FTRLSNP067 LOOP QUALIFICATION STATUS REQUIRED</p> <p>2. If not populated and the LNA field = "V" and the NPT field = "D" or "E" and the 2nd character of the LSR.ADMIN.TOS ="4" and the 3rd character of the LSR.ADMIN.TOS = "4" and the LSR.ADMIN.SLI = "C", "S" or "V", return error FTRLSNP132 LOOP QUALIFICATION STATUS REQUIRED</p> <p>3. If not populated and the LNA field = "V" and the NPT field = "D" or "E" and the 2nd character of the LSR.ADMIN.TOS = "W" or "X" and the 3rd character of the LSR.ADMIN.TOS = "-" and the LSR.ADMIN.SLI = "C", "S" or "V" return error FTRLSNP133 LOOP QUALIFICATION STATUS REQUIRED</p> <p>4. If populated and vv ="R" and LSR.ADMIN.SLI = "C" or "V" return error FTRLSNP068 A VALUE OF "R" IS PROHIBITED</p> <p>5. If populated and vv ≠ "R" or "C", return error FTRLSNP069 INVALID VALUE, ONLY R OR C ALLOWED.</p>	
34C	CBP1 - Cross Box Pair 1		N	1-4		<p>1.If not populated and CBCID is populated return error FTRLSNP070 CROSS BOX PAIR 1 REQUIRED WHEN THE CBCID FIELD IS POPULATED</p> <p>2.If populated and CBCID is not populated return</p>	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>error FTRLSNP071 CROSS BOX PAIR 1 PROHIBITED</p> <p>3. If populated and dl>4 return error FTRLSNP072 INVALID CROSS BOX PAIR 1 DATA LENGTH.</p> <p>4. If populated and dc ≠ numeric return error message FTRLSNP124 CBP1 MUST BE NUMERIC</p>	
34D	CBP2 - Cross Box Pair 2		N	1-4		<p>1.If not populated and CBCID2 is populated return error FTRLSNP073 CROSS BOX PAIR 2 REQUIRED WHEN THE CBCID2 FIELD IS POPULATED</p> <p>2. If populated and CBCID2 field is not populated return error FTRLSNP074 CROSS BOX PAIR 2 PROHIBITED WHEN THE CBCID2 FIELD IS NOT POPULATED.</p> <p>3. If populated and dl >4 return error FTRLSNP075 INVALID CBP2 DATA LENGTH.</p> <p>4. If populated and dc ≠ numeric return error message FTRLSNP129 CBP2 MUST BE NUMERIC</p>	O
35	JK CODE - Jack Code		A/N	1-5		<p>1. If populated and dl > 5 return error FTRLSNP076 INVALID JK CODE DATA LENGTH.</p>	O
36	IWT – Inside Wire Type	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD	
37	JK NUM - Jack Number		A/N	1-2		<p>1. If not populated and LSR.ADMIN.SLI ="H" and the 2nd character of the LSR.ADMIN.TOS = "1"return error FTRLSNP077 JACK NUMBER REQUIRED</p>	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						2. If populated and dl >2 return error FTRLSNP078 INVALID JACK NUMBER DATA LENGTH.	
38	JK POS - Jack Position		N	1-2		1. If not populated and LSR.ADMIN.SLI = "H" and the 2nd character of the LSR.ADMIN. TOS = "1" return error FTRLSNP079 JACK POSITION REQUIRED 2. If populated and dl >than 2 return error FTRLSNP080 INVALID JACK POSITION DATA LENGTH 3.If populated and vv ≠ numeric return error FTRLSNP081 INVALID JACK POSITION VALUE MUST BE NUMERIC.	O
39	JR - Jack Request	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
40	NIDR - NID Request		A	1-1	A B C	1. If not populated and the 2nd position of the LSR.ADMIN.TOS = "Z" return error FTRLSNP082 NID REQUEST IS REQUIRED 2. If populated and the 2nd position of the LSR.ADMIN TOS ≠ "Z" return error FTRLSNP083 NID REQUEST IS PROHIBITED 3. If populated and vv ≠ = A,B or C return error FTRLSNP084 INVALID NID REQUEST VALUE MUST = A,B OR C.	O
41	IWJK - Inside Wire Jack Code	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
42	IWJQ - Inside Wire Jack Quantity	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
43	PORTED NBR - Ported Telephone Number		N-HYPHEN	10-15	Range line numbers should be separated by	1.If populated and dl < 10 or >15 characters return error FTRLSNP085 INVALID PORTED NBR DATA LENGTH.	R

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
					a hyphen. For example: NNNNNNNNNN-NNNN.	<p>2.If populated and special characters present ≠ one hyphen return error FTRLSNP086 ONLY PORTED NBR SPECIAL CHARACTER ALLOWED IS ONE HYPHEN</p> <p>3. If not populated return error FTRLSNP087 PORTED NBR REQUIRED.</p> <p>4.If populated and dc ≠ numeric or numeric with 1 hyphen return error message FTRLSNP130 PORTED NBR CAN BE NUMERIC OR NUMERIC WITH ONE HYPEN..</p>	
44	TNP - Total Number of Paths	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
45	CFTN - Call Forward To Number	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
46	NPT - Number Portability Type		A	1-1	D= Local Routing Number/LNP E= Not Applicable P= Port Out Only	<p>1. If populated and dc ≠ D, E or P return error FTRLSNP088 INVALID NPT VALUE CAN BE D OR E OR P ONLY.</p> <p>2. If not populated return error FTRLSNP089 NPT REQUIRED.</p>	R
47	RTI - Route Index	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
48	NPTG - Number Portability Trunk Group	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
49	LSCP - Local Service Provider Change Prohibited	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
50	BA - Blocking Activity	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
51	BLOCK - Block	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
52	FPI - Freeze PIC	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF	

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
	Indicator					THIS FIELD ON THIS FORM	
53	LPIC - IntraLATA Presubscription Indicator Code	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
54	TC OPT - Transfer of Call Options		A	1-1	N= None S= Standard T= Split Transfer of Calls	1. If not populated and NPT field = "E", return error FTRLSNP090 TC OPT REQUIRED WHEN THE NPT FIELD EQUALS "E" If populated and NPT field ≠ "E", return error FTRLSNP091 TC OPT PROHIBITED WHEN THE NPT FIELD DOES NOT EQUAL "E". If populated and vv ≠ N or S or T return error FTRLSNP092 ONLY VALID TC OPT VALUES ARE N OR S OR T.	O
TCTOPRIMARYSECTION							
55	TC TO PRI - Transfer of Calls To Primary Number		N	10-10		1. If not populated and the TC OPT field is "S" or "T", return error FTRLSNP093 TC TO PRI REQUIRED. 2. If populated and the TC OPT field is not "S" or "T", return error FTRLSNP094 TC TO PRI PROHIBITED 3. If populated and dl ≠ 10 characters return error message FTRLSNP095 TC TO PRI MUST BE 10 CHARACTERS 4. If populated and vv ≠ numeric return error Message FTRLSNP034 VALID TC TO PRI VALUE CAN ONLY BE NUMERIC.	O
57	TCID - Transfer of Calls To Identifier		N	1-2		1. If not populated and TC OPT = "T", return error message FTRLSNP099 TRANSFER OF	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						CALLS TO IDENTIFIER REQUIRED 2. If populated and TC OPT ≠ "T", return error message FTRLSNP100 TRANSFER OF CALLS TO IDENTIFIER PROHIBITED 3.If populated and dl >2 characters return error FTRLSNP101 INVALID TCID DATA LENGTH. 4. If populated and dc ≠ numeric return error FTRLSNP102 INVALID TCID DATA MUST BE NUMERIC.	
58	TC NAME - Transfer of Calls To Name		A/N Apostrophe, Hyphen, Comma, Space.	1-35		1. If not populated and TC OPT = "T", return error message FTRLSNP103 TRANSFER OF CALLS TO NAME REQUIRED 2.If populated and TC OPT ≠"T", return error message FTRLSNP104 TRANSFER OF CALLS TO NAME PROHIBITED 3. If populated and dl >35 return error FTRLSNP105 INVALID TC NAME DATA LENGTH 4. If populated and any special characters ≠ Apostrophe, Hyphen, Comma, Space return error FTRLSNP106 INVALID TC NAME DATA, ONLY SPECIAL CHARACTERS ALLOWED ARE APOSTROPHE, HYPHEN, COMMA, SPACE	O
TCTOSECONDARYSECTION							
56	TC TO SEC - Transfer of Calls To Secondary Number		N	10-10		1. If not populated TC OPT = "T", return error message FTRLSNP096 TRANSFER OF CALLS TO SECONDARY NUMBER REQUIRED	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>2. If populated and TC OPT ≠ "T", return error message FTRLSNP097 TRANSFER OF CALLS TO SECONDARY NUMBER PROHIBITED</p> <p>3. If populated dl ≠ 10 characters return error FTRLSNP098 INVALID TC TO SEC DATA LENGTH</p> <p>4. If populated and vv ≠ numeric return error message FTRLSNP049 TC TO SEC MUST BE NUMERIC</p>	
58A	TCID 2 - Transfer of Calls To Identifier 2		N	1-2		<p>1. If not populated and TC OPT = "T", return error message FTRLSNP107 TRANSFER OF CALLS TO IDENTIFIER 2 REQUIRED</p> <p>2. If populated and TC OPT ≠ "T", return error message FTRLSNP108 TRANSFER OF CALLS TO IDENTIFIER 2 PROHIBITED</p> <p>3. If populated and dc ≠ numeric return error FTRLSNP109 INVALID TCID 2 DATA MUST BE NUMERIC</p> <p>4. If populated and dl > 2 return error FTRLSNP110 INVALID TCID 2 DATA LENGTH</p>	O
58B	TCNAME 2 - Transfer of Calls To Name 2		A/N Apostrophe, Hyphen, Comma, Space.	1-35		<p>1. If not populated and TC OPT = "T", return error message FTRLSNP111 TRANSFER OF CALLS TO NAME 2 REQUIRED</p> <p>2. If populated and TC OPT ≠ "T", return error message FTRLSNP112 TRANSFER OF CALLS TO NAME 2 PROHIBITED</p>	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						3. If populated and dl > 35 return error FTRLSNP113 INVALID TCNAME 2 DATA LENGTH 4. If populated and any special characters ≠ Apostrophe, Hyphen, Comma, Space return error FTRLSNP114 INVALID TCNAME 2 DATA, ONLY SPECIAL CHARACTERS ALLOWED ARE APOSTROPHE, HYPHEN, COMMA, SPACE	
59	TC PER - Transfer of Calls Period		N	8-8	Value- Valid Entries Metric Format Two Digit Century (00-99) Two Digit Year (00-99) Two Digit Month (01-12) Two Digit Day (01-31)	1. If populated and TC TO PRI field is not populated, return error FTRLSNP115 TRANSFER OF CALLS PERIOD PROHIBITED 2. Deleted Rule 3. If populated and dl ≠ 8 characters return error FTRLSNP117 INVALID TC PER DATA LENGTH. 4. If populated and vv is not > or = to LSR.ADMIN.DDD return error FTRLSNP118 TC PER DATE MUST BE GREATER OR EQUAL TO VALUE ON THE LSR ADMIN DDD. 5. If populated and positions 5 and 6 ≠ 01 to 12 return error FTRLSNP126 TC PER MONTH MAY ONLY BE.01-12. 6. If populated and positions 7 and 8 ≠ 01-31 return error FTRLSNP127 TC PER DAY CAN ONLY BE 01-31. 7. If populated and dc ≠ numeric return error message FTRLSNP128 TC PER MUST BE 8	O

Field Number	Field Name	Mapping Rule	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						NUMERIC CHARACTERS – ALPHAS OR SPECIAL CHARACTERS NOT ALLOWED	
59A	TCMESS 1 - Transfer of Calls Message		A/N Ampersand, Apostrophe, Dollar Sign, Virgule, Hyphen, Number Sign, Parentheses, Comma, Quotation Marks, Space.	1-12		<p>1. If populated and LSR.ADMIN.ACT ="V" and the LNA field ≠ "D", return error message FTRLSNP119 TRANSFER OF CALLS MESSAGE PROHIBITED</p> <p>2. If populated and special characters ≠ Ampersand, Apostrophe, Dollar Sign, Virgule, Hyphen, Number Sign, Parentheses, Comma, Quotation Marks, Space return error FTRLSNP120 INVALID DATA, ONLY SPECIAL CHARACTERS ALLOWED ARE AMPERSAND, APOSTROPHE, DOLLAR SIGN, VIRGULE, HYPHEN, NUMBER SIGN, PARENTHESES, COMMA, QUOTATION MARKS, SPACE.</p> <p>3. If populated and dl > than 12 characters return error FTRLSNP121 INVALID TCMESS 1 DATA LENGTH.</p>	O
60	LEAN - Line Existing Account Number	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
61	LEATN - Line Existing Account Telephone Number	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	
62	REMARKS - Remarks	DO NOT MAP				FRONTIER DOES NOT SUPPORT THE USE OF THIS FIELD ON THIS FORM	

APPENDIX A: ERROR MESSAGES

Error Message Number	Error Message Text
FTRLSNP001	INVALID LOOP QUANTITY DATA LENGTH.
FTRLSNP002	INVALID DATA LOOP QUANTITY MUST BE NUMERIC
FTRLSNP003	LOOP QUANTITY REQUIRED
FTRLSNP004	INVALID DATA NPQTY LENGTH
FTRLSNP005	INVALID NPQTY DATA, MUST BE NUMERIC.
FTRLSNP006	INVALID LOCNUM DATA LENGTH.
FTRLSNP007	INVALID DATA, LOCNUM MUST BE NUMERIC.
FTRLSNP008	NPQTY REQUIRED
FTRLSNP009	LOCNUM REQUIRED.
FTRLSNP010	INVALID LNUM LENGTH MAY NOT EXCEED 5 CHARACTERS.
FTRLSNP011	INVALID DATA, LNUM MUST BE NUMERIC.
FTRLSNP012	LNUM REQUIRED.
FTRLSNP013	ONLY VALID VALUE A.
FTRLSNP014	ONLY LNA VALID VALUE D OR V.
FTRLSNP015	CUSTOMER CIRCUIT REFERENCE REQUIRED
FTRLSNP016	INVALID DATA LENGTH CKR CANNOT EXCEED 41 CHARACTERS.
FTRLSNP017	THE ONLY CKR CHARACTERS ALLOWED ARE A/N AMPERSAND, APOSTROPHE, ASTERISK, PARENTHESES, COLON, COMMA, DOLLAR SIGN, HYPHEN, NUMBER SIGN, PERCENT, PLUS SIGN, QUOTE, SEMICOLON, SPACE, PERIOD
FTRLSNP018	REUSE LOOP REQUIRED
FTRLSNP019	REUSE LOOP PROHIBITED
FTRLSNP020	INVALID REUSE LOOP VALUE MUST BE Y.
FTRLSNP021	OECCKT REQUIRED WHEN REUSE FIELD IS POPULATED.
FTRLSNP022	OECCKT PROHIBITED WHEN REUSE LOOP FIELD NOT POPULATED.
FTRLSNP023	ONLY OECCKT SPECIAL CHARACTERS ALLOWED ARE VIRGULES.
FTRLSNP024	INVALID OECCKT DATA LENGTH
FTRLSNP025	TELECOMMUNICATIONS SERVICE PRIORITY PROHIBITED
FTRLSNP026	ONLY SPECIAL TSP DATA CHARACTERISTICS ALLOWED IS HYPHEN
FTRLSNP027	TSP INVALID DATA LENGTH
FTRLSNP028	INVALID FOR STATE
FTRLSNP029	TNT PROHIBITED

Error Message Number	Error Message Text
FTRLSNP030	INVALID TNT VALUE. ONLY VALUE CAN BE D
FTRLSNP031	INVALID LRN DATA LENGTH.
FTRLSNP032	INVALID LRN DATA CHARACTERISTIC. MUST BE NUMERIC
FTRLSNP033	INVALID VALUE TNT ONLY VALID VALUE Y
FTRLSNP034	VALID TC TO PRI VALUE CAN ONLY BE NUMERIC
FTRLSNP035	SAN CANNOT EXCEED 30 CHARACTERS.
FTRLSNP036	CFA REQUIRED
FTRLSNP037	INVALID CFA DATA LENGTH
FTRLSNP038	ONLY CFA SPECIAL CHARACTERS ALLOWED ARE HYPHEN, PERIOD, AND SPACE.
FTRLSNP039	CONNECTION TYPE INDICATOR PROHIBITED
FTRLSNP040	VALID CTI VALUE B
FTRLSNP041	SYSTEM ID REQUIRED.
FTRLSNP042	SYSTEM ID PROHIBITED.
FTRLSNP043	SYSTEM ID MUST BE 5 CHARACTERS 3 ALPHA FOLLOWED BY 2 NUMERIC.
FTRLSNP044	SYSTEM ID MUST BE 3 ALPHA FOLLOWED BY 2 NUMERIC.
FTRLSNP045	CABLE ID REQUIRED.
FTRLSNP046	CABLE ID PROHIBITED
FTRLSNP047	CABLE ID MUST BE 5 CHARACTERS
FTRLSNP048	INVALID DATA SLOT LENGTH
FTRLSNP049	TC TO SEC MUST BE NUMERIC.
FTRLSNP050	INVALID CABLE ID DATA THE ONLY SPECIAL CHARACTERS ALLOWED ARE AMPERSAND, APOSTROPHE, ASTERISK, COLON, COMMA, DOLLAR SIGN, HYPHEN, NUMBER SIGN, PARENTHESES, PERIOD, QUOTATION MARKS, SPACE, PERCENT SIGN, PLUS SIGN, SEMICOLON, VIRGULE, AT SIGN
FTRLSNP051	CROSS BOX CABLE IDENTIFICATION REQUIRED
FTRLSNP052	CROSS BOX CABLE IDENTIFICATION PROHIBITED
FTRLSNP053	INVALID CROSS BOX CABLE IDENTIFICATION DATA LENGTH
FTRLSNP054	CROSS BOX CABLE IDENTIFICATION 2 REQUIRED
FTRLSNP055	CROSS BOX CABLE IDENTIFICATION 2 PROHIBITED
FTRLSNP056	INVALID CBCID2 DATA LENGTH
FTRLSNP057	SHELF REQUIRED
FTRLSNP058	SHELF PROHIBITED.
FTRLSNP059	SHELF MUST BE 2 NUMERIC

Error Message Number	Error Message Text
FTRLSNP060	CHAN/PAIR REQUIRED
FTRLSNP061	CHAN/PAIR PROHIBITED.
FTRLSNP062	CHAN/PAIR MUST BE 5 CHARACTERS.
FTRLSNP063	CHAN/PAIR MUST BE IN RANGE OF 00001 - 09999
FTRLSNP064	CHAN/PAIR MUST BE IN RANGE OF 00001 - 00999.
FTRLSNP065	RESZONE PROHIBITED
FTRLSNP066	RESZONE VALID VALUE IS Y
FTRLSNP067	LOOP QUALIFICATION STATUS REQUIRED
FTRLSNP068	A VALUE OF "R" IS PROHIBITED
FTRLSNP069	INVALID VALUE, ONLY R OR C ALLOWED.
FTRLSNP070	CROSS BOX PAIR 1 REQUIRED WHEN THE CBCID FIELD IS POPULATED
FTRLSNP071	CROSS BOX PAIR 1 PROHIBITED
FTRLSNP072	INVALID CROSS BOX PAIR 1 DATA LENGTH
FTRLSNP073	CROSS BOX PAIR 2 REQUIRED WHEN THE CBCID2 FIELD IS POPULATED
FTRLSNP074	CROSS BOX PAIR 2 PROHIBITED WHEN THE CBCID2 FIELD IS NOT POPULATED
FTRLSNP075	INVALID CBP2 DATA LENGTH
FTRLSNP076	INVALID JK CODE DATA LENGTH
FTRLSNP077	JACK NUMBER REQUIRED
FTRLSNP078	INVALID JACK NUMBER DATA LENGTH
FTRLSNP079	JACK POSITION REQUIRED
FTRLSNP080	INVALID JACK POSITION DATA LENGTH
FTRLSNP081	INVALID JACK POSITION VALUE MUST BE NUMERIC.
FTRLSNP082	NID REQUEST IS REQUIRED
FTRLSNP083	NID REQUEST IS PROHIBITED
FTRLSNP084	NID REQUEST VALUE MUST = A,B OR C
FTRLSNP085	INVALID PORTED NBR DATA LENGTH
FTRLSNP086	ONLY PORTED NBR SPECIAL CHARACTER ALLOWED IS ONE HYPHEN
FTRLSNP087	PORTED NBR REQUIRED.
FTRLSNP088	INVALID NPT VALUE CAN BE D OR E OR P ONLY
FTRLSNP089	NPT REQUIRED
FTRLSNP090	TC OPT REQUIRED WHEN THE NPT FIELD EQUALS "E"
FTRLSNP091	TC OPT PROHIBITED WHEN THE NPT FIELD DOES NOT EQUAL"E"
FTRLSNP092	ONLY VALID TC OPT VALUES ARE N OR S OR T
FTRLSNP093	TC TO PRI REQUIRED

Error Message Number	Error Message Text
FTRLSNP094	TC TO PRI PROHIBITED
FTRLSNP095	TC TO PRI MUST BE 10 CHARACTERS
FTRLSNP096	TRANSFER OF CALLS TO SECONDARY NUMBER REQUIRED
FTRLSNP097	TRANSFER OF CALLS TO SECONDARY NUMBER PROHIBITED
FTRLSNP098	INVALID TC TO SEC DATA LENGTH
FTRLSNP099	TRANSFER OF CALLS TO IDENTIFIER REQUIRED
FTRLSNP100	TRANSFER OF CALLS TO IDENTIFIER PROHIBITED
FTRLSNP101	INVALID TCID DATA LENGTH
FTRLSNP102	INVALID TCID DATA MUST BE NUMERIC
FTRLSNP103	TRANSFER OF CALLS TO NAME REQUIRED
FTRLSNP104	TRANSFER OF CALLS TO NAME PROHIBITED
FTRLSNP105	INVALID TC NAME DATA LENGTH
FTRLSNP106	INVALID TC NAME DATA, ONLY SPECIAL CHARACTERS ALLOWED ARE APOSTROPHE, HYPHEN, COMMA, SPACE
FTRLSNP107	TRANSFER OF CALLS TO IDENTIFIER 2 REQUIRED
FTRLSNP108	TRANSFER OF CALLS TO IDENTIFIER 2 PROHIBITED
FTRLSNP109	INVALID TCID 2 DATA MUST BE NUMERIC
FTRLSNP110	INVALID TCID 2 DATA LENGTH.
FTRLSNP111	TRANSFER OF CALLS TO NAME 2 REQUIRED
FTRLSNP112	TRANSFER OF CALLS TO NAME 2 PROHIBITED
FTRLSNP113	INVALID TCNAME 2 DATA LENGTH
FTRLSNP114	INVALID TCNAME 2 DATA, ONLY SPECIAL CHARACTERS ALLOWED ARE APOSTROPHE, HYPHEN, COMMA, SPACE
FTRLSNP115	TRANSFER OF CALLS PERIOD PROHIBITED
FTRLSNP116	
FTRLSNP117	INVALID TC PER DATA LENGTH.
FTRLSNP118	TC PER DATE MUST BE GREATER OR EQUAL TO VALUE ON THE LSR ADMIN DDD
FTRLSNP119	TRANSFER OF CALLS MESSAGE PROHIBITED
FTRLSNP120	INVALID DATA, ONLY SPECIAL CHARACTERS ALLOWED ARE AMPERSAND, APOSTROPHE, DOLLAR SIGN, VIRGULE, HYPHEN, NUMBER SIGN, PARENTHESES, COMMA, QUOTATION MARKS, SPACE
FTRLSNP121	INVALID TCMESS 1 DATA LENGTH
FTRLSNP122	SLOT IS PROHIBITED
FTRLSNP123	INVALID DATA RELAY RACK LENGTH

Error Message Number	Error Message Text
FTRLSNP124	CBP1 MUST BE NUMERIC
FTRLSNP125	CTI REQUIRED
FTRLSNP126	TC PER MONTH MAY ONLY BE 01-12
FTRLSNP127	TC PER DAY CAN ONLY BE 01-31
FTRLSNP128	TC PER MUST BE 8 NUMERIC CHARACTERS ALPHAS OR SPECIAL CHARACTERS NOT ALLOWED
FTRLSNP129	CBP2 MUST BE NUMERIC
FTRLSNP130	PORTED NBR CAN BE NUMERIC OR NUMERIC WITH ONE HYPEN
FTRLSNP131	SHELF MUST BE 2 NUMERIC CHARACTERS
FTRLSNP132	LOOP QUALIFICATION STATUS REQUIRED
FTRLSNP133	LOOP QUALIFICATION STATUS REQUIRED
FTRLSNP134	LNA REQUIRED
FTRLSNP135	THE ONLY CHARACTERS ALLOWED ARE A/N AMPERSAND, APOSTROPHE, ASTERISK, PARENTHESES, COLON, COMMA, DOLLAR SIGN, HYPHEN, NUMBER SIGN, PERCENT, PLUS SIGN, QUOTE, SEMICOLON, SPACE.
FTRLSNP136	CTI REQUIRES SYSTEM ID, SHELF AND CHAN/PAIR
FTRLSNP137	CTI REQUIRES CABLE ID AND CHAN/PAIR
FTRLSNP138	
FTRLSNP139	
FTRLSNP140	

